

## Fonet opsætning af IP-telefon på WLAN 7270 SIP-proxy

Efter din WLAN 7270 er opgraderet til firmware: Version 54.04.76

kan du følge nedenstående for at registrerer dine IP-telefoner forbundet via LAN eller WLAN.

## Gå ind under Telephony

🏉 FRITZ!	Box - Windows Internet Explorer												
$\bigcirc \bigcirc$	✓				👻 🐓 🗙 🛛 silkeborg bio	۶ ج							
🚖 🎄	😬 🔹 FONET IP telef 🔯 jp.dk - Forsiden 👔	Forside   Norde 📀 FONET IP telef 👔	🖉 Voipsnak.dk 👔	FRITZ!Box × 🔏 Grand	Istream D 🔄 🔹 🔊 💌 🖶 👻 Side 🕶	③ F <u>u</u> nktioner ▼							
AVG	AVG 🕆 🔽 fitz.box 🗸 Search 🔶 🖏 Total Protection 🛛 🖓 AVG Info - Get More 👘 -												
	FRITZ/Box												
		Start Menu	Settings		🏠 📴 😭 🖶 💡								
	Telephony Devices Overview Fixed Line												
	Wizards												
	Advanced Settings     On this page you can configure and edit the telephones, answering machines and fax machines connected to the     FRITZIBox.												
	- Telephony	Name	Port	Number									
	Calls	Basic ISDN settings	FON S0										
	Telephone book	Fon 1	FON 1	77344141									
	Alarm	Fon 2	FON 2	77344141									
	Call Diversion	IP Telephone 1 via SIP pr	roxy LAN/WLAN	77344141									
	Telephony Devices	Kontor B&O	DECT	77344141									
	Dialing Rules	Kontor Motorola	DECT	77344141									
	Regional Options												
	► USB devices			Configure	e New Device Help								
	<ul> <li>Storage (NAS)</li> </ul>												
	► WLAN												
	+ DECT												
	> System												
	Programs												
7.		N	)II. —	J		~							

Vælg: Configure New Devices



## Tryk: Next



Vælg: LAN/WLAN (IP Telephone)



Indtast et navn på telefonen og tryk Next



Her ser du det lokalnummer telefonen har fået (her 621).

Vælg et SIP password

I din IP-telefon skal du så indlægge: SIP Registrar: fritz.box SIP Password: den valgte kode

Når du har indlagt dette og foretaget Reboot på IP-telefonen

Tryk next



Afvent registrering



Registrering er nu OK



Vælg hvilket telefonnummer den skal anvende ved udgående opkald (og hermed din Fonet konto) Tryk Next



Vælg hvilket/hvilke telefonnumre der skal besvares ved indgående opkald. Tryk Next



Tryk Apply

🥖 Grandstream Device Configuration - W	/indows Internet Explorer									
🚱 🕞 👻 🙋 http://192.168.178.28/cd	onfig_a3.htm			• 4 <sub>7</sub> ×	🕻 silkeborg bio 🖉 👻					
🙀 🏟 🔡 🗸 💋 FONET IP telef	ጁ jp.dk - Forsiden 👔 Forside   Norde 📀 FONE	IP telef	🖉 Voipsnak.dk 🍃 F	RITZ!Box 🌈 Grandstrea 🗙 🏠 🔻 🖡	🛐 👻 🖶 💌 📝 Side 💌 🍈 Funktioner 💌					
VG 🗸 🖅 gxp2000-ff 🔹 Search 🖗 🕄 Total Protection 🛛 🖓 AVG Info - Get More 🖓 -										
			1		_					
	Gra	ndstream	n Device Configur	ation						
	STATUS BASIC SETTINGS ADVANCED									
	Account Active:	No	Yes							
	Account Name:			(e.g., MyCompany)						
	SIP Server:	fritz.box		(e.g., sip.mycompany.com, or IP address)						
	Outbound Proxy:			(e.g., proxy.myprovider.com, or IP address)						
	SIP User ID:	621		(the user part of an SIP address)	=					
	Authenticate ID:	-		(can be same or different from SIP UserID)						
	Authenticate Password:			(not displayed for security protection)						
	Name:	gxp2000-I	line 3	(optional, e.g., John Doe)						
	Use DNS SRV:	No	O Yes							
	User ID is phone number:	No	Yes							
	SIP Registration:	No	Yes							
	Unregister On Reboot:	No	O Yes							
	Register Expiration:		(in minutes. default 1	hour, max 45 days)						
	local SIP port:	5064 (default 5064)								
	SIP Registration Failure Retry Wait Time:		(in seconds. Between							
	SIP T1 Timeout:	1 sec 🔻								
	SIP T2 Interval:	4 sec ▼								
	SIP Transport:	• UDP	● TCP							
	Use RFC3381 Symmetric Routing:	No	<ul> <li>Yes</li> <li>No but condition</li> </ul>	atara 🔿 Vas						
	SUBSCRIBE for MWI:	No	<ul> <li>No, but send keep</li> <li>Ves</li> </ul>	-anve U res						
	PUBLISH for Presence:	No	<ul> <li>Yes</li> </ul>							
	Proxy-Require:									
	Voice Mail UserID:			(UserID for voice mail system)						
	Send DTMF:	✓ in-aud	tio 🔲 via RTP (RFC	(2833) via SIP INFO						
	Early Dial:	No	Yes (use "Yes" or	nly if proxy supports 484 response)						
	Dial Plan Prefix:		(this prefix string is ad	lded to each dialed number)						
	Delayed Call Forward Wait Time:	20	(Allowed range 1-12	0, in seconds.)						
					· · · · · · · · · · · · · · · · · · ·					

Her ser du et eksempel på opsætning af en GXP2000 telefon:

Når der ringes lokalt <u>mellem</u> IP-telefonerne registreret på fritz.box skal man taste:

\*\*<lokalnummer> Eks.: \*\*621

Hermed benyttes og belastes kun dit lokale netværk!