

## FONET – Opsætning af Linksys SPA921

080908

Brugernavn (Username) og Adgangskode (password) finder du på din personlige konto under punktet – Lokalnumre.

Husk at du kun må anvende Brugernavn og Adgangskode på én opsætning!

Du kan med fordel anvende 'Klip&Indsæt', men se godt efter, at der ikke kommer et mellemrum for meget eller mangler noget!

The screenshot shows the FONET website interface. At the top, there's a navigation bar with links: Forside, Produkter, Abonnement, Priser, Information, eButik, Om FONET, Links, Support. The main heading is "Bredbåndstelefon: Bedre-Billigt-Brugervenligt".

**Left Sidebar (Mine Sider):**

- Dit navn
- Personlige Data
- Konto opsætning
- Transaktioner
- Kortnumre
- Lokalnumre
- Telefonnumre
- Viderestilling
- Netto-Kald
- eFaktura
- Tankning
- Log Ud

**Tip:** dine venner og få DKK 29 til samtaler, når de opretter et PLUS-abonnement! [Tip-en-Ven](#)

**Main Content:**

**Bredbåndstelefon: Bedre-Billigt-Brugervenligt**

Med Netto-Kald tilbyder FONET billig telefoni til ALLE telefonabonnenter i Danmark - Læs mere her!

**Gratis oprettelse og PLUS-abonnement med Netto-Kald i 6 måneder ved køb af introduktionstilbud.**

Med et FONET PLUS-abonnement foretager du dine samtaler på samme måde som i dag. Blot foretages de nu via dit bredbåndsabonnement. Slip for det dyre telefonabonnement, behold dit telefonnummer, få flere services og en lettere hverdag og ekstremt lave minutpriser!

**Opkald mellem globale FONET abonnenter er gratis!**

Med FONET er det enkelt, derfor gælder minutprisen døgnet rundt, og du betaler kun for de sekunder samtalen varer:

Dansk Fastnet	10 øre / minut
Dansk Mobilnet	80 øre / minut

Vælger du at købe en FONET IP-telefon eller en adapter til din nuværende telefon behøver din PC ikke at være tændt! Dit FONET PLUS-abonnement giver et fastnet nummer og 2 telefonlinier, der vel at mærke ikke behøver at være på samme adresse. Så ta' den ene med på arbejde, i sommerhuset eller på rejse.

Med FONET har du mulighed for selv at administrere dine funktioner, så de til enhver tid er tilpasset dit behov.

**Med et FONET PLUS-abonnement får du følgende services:**

- Kortnummer Valg (100)
- Vis Nummer
- Banker-på
- Telefonsvarer
- Samtalespecifikation
- Netto-Kald
- Genkald
- Viderestilling
- Fast Modtager
- Forstyr-ikke
- \* Flere services på vej

**PLUS-Abonnement**

- Gratis oprettelse
- Gratis samtaler
- Fastnetsamtaler
- Personlig konto
- FONET services
- Netto-Kald abonnement
- Et fastnet telefonnr.
- To linier med egne lokalnr.
- Overfl. telefonnr. (DKK 200)
- DKK 29 pr. måned**

**Introduktionstilbud**

PLUS-abonnement i 6 måneder

Et fastnet telefonnummer

To linier

100 min. dansk fastnet

Inklusiv:

IP-Adapter	IP-telefon
DKK 595	DKK 695

[Tilmeld dig her](#)

**Netto-Kald**

Har du ikke bredbånd, men blot ønsker at kunne ringe billigt fra din mobil- eller stue-telefon kan du tegne et separat Netto-Kald abonnement.

**DKK 10 pr. måned**

[Tilmeld dig her](#)

The bottom of the screenshot shows the Windows taskbar with various open applications like Internet Explorer, Outlook, and Paint.

FONET IP telefoni - Packard Bell

Filer Rediger Vis Foretrukne Funktioner Hjælp

Tilbage Søg Foretrukne

Adresse <https://www.fonet.dk/> Search 0 blocked Check AutoLink AutoFill Options

**FONET™** Bredbånd der er til at tale med™

Forside Produkter Abonnement Priser Information eButik Om FONET Links Support

**Lokalnumre**

Lokalnummer	Brugernavn	Adgangskode
44141*1	_NQ_hn	6Hug3
44141	_NQ_hn	bhDo

**Mine Sider**

Dit navn

Personlige Data  
konto opsætning  
Transaktioner  
Kortnumre  
Lokalnumre  
Telefonnumre  
Viderestilling  
Netto-Kald  
eFaktura  
Tankning  
Log Ud

Udført Internetet



Sipura SPA Configuration - Packard Bell

FilerRedigerVisForetrukneFunktionerHjælp

Tilbage

Adresse

http://192.168.15.102/admin/advanced

Go

Google

Bookmarks

14 blocked

Check

AutoLink

AutoFill

Send to

Settings

SIPURA

technology, inc.

Sipura Telephone Configuration

InfoSystemSIPProvisioningRegionalPhoneExt 1User

User Login

basic

advanced

Personal Directory

Call History

Call Progress Tones

Dial Tone:

350@-19,440@-19;10(\*0/1+2)

Outside Dial Tone:

420@-16;10(\*0/1)

Prompt Tone:

520@-19,620@-19;10(\*0/1+2)

Busy Tone:

480@-19,620@-19;10(.5/.5/1+2)

Reorder Tone:

480@-19,620@-19;10(.25/.25/1+2)

Off Hook Warning Tone:

480@-10,620@0;10(.125/.125/1+2)

Ring Back Tone:

440@-19,480@-19;\*(2/4/1+2)

Call Waiting Tone:

440@-10;30(.3/9.7/1)

Confirm Tone:

600@-16;1(.25/.25/1)

SIT1 Tone:

905@-16,1420@-16;1777@-16;20(.300/0/1,,300/0/2,,300/0/3,0/4/0)

SIT2 Tone:

914@-16,1371@-16;1777@-16;20(.274/0/1,,274/0/2,,380/0/3,0/4/0)

SIT3 Tone:

914@-16,1371@-16;1777@-16;20(.380/0/1,,380/0/2,,380/0/3,0/4/0)

SIT4 Tone:

985@-16,1371@-16;1777@-16;20(.380/0/1,,274/0/2,,380/0/3,0/4/0)

MWI Dial Tone:

350@-19,440@-19;2(.1/1/1+2);10(\*0/1+2)

Cfwd Dial Tone:

350@-19,440@-19;2(.2/2/1+2);10(\*0/1+2)

Holding Tone:

600@-19;25(.1/1/1,,1/1/1,,1/9.5/1)

Conference Tone:

350@-19;20(.1/1/1,,1/9.7/1)

Secure Call Indication Tone:

397@-19,507@-19;15(0/2/0,,2/1/1,,1/2.1/2)

Page Tone:

600@-16;3(.05/0.05/1)

Distinctive Ring Patterns

Cadence 1:

60(2/4)

Cadence 2:

60(.3/2,1/2,,3/4)

Cadence 3:

60(.8/4,,8/4)

Cadence 4:

60(.4/2,,3/2,,8/4)

Cadence 5:

60(.2/2,,2/2,,2/2,1/4)

Cadence 6:

60(.2/4,,2/4,,2/4)

Cadence 7:

60(4.5/4)

Cadence 8:

60(0.25/9.75)

Control Timer Values (sec)

Reorder Delay:

5

Call Back Expires:

1800

Call Back Retry Intvl:

30

Call Back Delay:

.5

Interdigit Long Timer:

10

Interdigit Short Timer:

3

Vertical Service Activation Codes

Call Return Code:

\*69

Blind Transfer Code:

\*98

Call Back Act Code:

\*66

Call Back Deact Code:

\*86

Cfwd All Act Code:

\*72

Cfwd All Deact Code:

\*73

Start

D:\Documents a...

Inbox - Microso...

FONET IP telefo...

Sipura SPA Co...

https://www.on...

jp.dk - JP - Pack...

Document1 - Mi...

Document3 - Mi...

Internet

10:09

Sipura SPA Configuration - Packard Bell

FilerRedigerVisForetrukneFunktionerHjælp

TilbageSøgForetrukne

Adressehttp://192.168.15.102/admin/advancedGo

GoogleBookmarks14 blockedCheckAutolinkAutoFillSend toSettings

Control timer values (sec)

Reorder Delay:5

Call Back Expires:1800

Call Back Retry Intvl:30

Call Back Delay:.5

Interdigit Long Timer:10

Interdigit Short Timer:3

Vertical Service Activation Codes

Call Return Code:\*69

Blind Transfer Code:\*98

Call Back Act Code:\*66

Call Back Deact Code:\*86

Cfwd All Act Code:\*72

Cfwd All Deact Code:\*73

Cfwd Busy Act Code:\*90

Cfwd Busy Deact Code:\*91

Cfwd No Ans Act Code:\*92

Cfwd No Ans Deact Code:\*93

Block CID Act Code:\*67

Block CID Deact Code:\*68

Block CID Per Call Act Code:\*81

Block CID Per Call Deact Code:\*82

Block ANC Act Code:\*77

Block ANC Deact Code:\*87

DND Act Code:\*78

DND Deact Code:\*79

Secure All Call Act Code:\*16

Secure No Call Act Code:\*17

Secure One Call Act Code:\*18

Secure One Call Deact Code:\*19

Paging Code:\*96

Call Park Code:\*38

Call Pickup Code:\*36

Call UnPark Code:\*39

Group Call Pickup Code:\*37

Referral Services Codes:

Feature Dial Services Codes:

Outbound Call Codec Selection Codes

Prefer G711u Code:\*017110

Force G711u Code:\*027110

Prefer G711a Code:\*017111

Force G711a Code:\*027111

Prefer G723 Code:\*01723

Force G723 Code:\*02723

Prefer G726r16 Code:\*0172616

Force G726r16 Code:\*0272616

Prefer G726r24 Code:\*0172624

Force G726r24 Code:\*0272624

Prefer G726r32 Code:\*0172632

Force G726r32 Code:\*0272632

Prefer G726r40 Code:\*0172640

Force G726r40 Code:\*0272640

Prefer G729a Code:\*01729

Force G729a Code:\*02729

Miscellaneous

Set Local Date (mm/dd):

Set Local Time (HH/mm):

Time Zone:GMT+01:00

Time Offset (HH/mm):

Daylight Saving Time Rule:

DTMF Playback Level:-16

DTMF Playback Length:.1

Inband DTMF Boost:12dB

Undo All Changes

Submit All Changes

User Loginbasicadvanced

Copyright © 2003-2005 Sipura Technology. All Rights Reserved.

StartD:\Documents a...Inbox - Microso...FONET IP telefo...Sipura SPA Co...https://www.on...jp.dk - JP - Pack...Document1 - Mi...Document3 - Mi...Internet10:10

**SIPURA**  
technology, inc.

## Sipura Telephone Configuration

Info System SIP Provisioning Regional Phone **Ext 1** User

[User Login](#) [basic](#) | [advanced](#)  
[Personal Directory](#) [Call History](#)

**General**

Line Enable:

**Share Line Appearance**

Share Ext:  Shared User ID:

Subscription Expires:

**NAT Settings**

NAT Mapping Enable:  NAT Keep Alive Enable:

NAT Keep Alive Msg:  NAT Keep Alive Dest:

**Network Settings**

SIP TOS/DiffServ Value:  SIP CoS Value:

RTP TOS/DiffServ Value:  RTP CoS Value:

Network Jitter Level:  Jitter Buffer Adjustment:

**SIP Settings**

SIP Port:  SIP 100REL Enable:

EXT SIP Port:

Auth Resync-Reboot:

SIP Proxy-Require:

SIP Remote-Party-ID:

Referor Bye Delay:  Refer-To Target Contact:

Referee Bye Delay:  SIP Debug Option:

Refer Target Bye Delay:  Sticky 183:

**Call Feature Settings**

Blind Attn-Xfer Enable:  MOH Server:

Message Waiting:  Auth Page:

Default Ring:  Auth Page Realm:

Conference Bridge URL:  Auth Page Password:

Mailbox ID:  Voice Mail Server:

State Agent:  CFWD Notify Serv:

CFWD Notifier:

**Proxy and Registration**

Proxy:  Use Outbound Proxy:

Start | D:\Documents a... | Inbox - Microso... | FONET IP telefo... | **Sipura SPA Co...** | https://www.on... | jp.dk - JP - Pack... | Document1 - Mi... | Document3 - Mi... | 10:10

Sipura SPA Configuration - Packard Bell

Filer Rediger Vis Foretrukne Funktioner Hjælp

Adresse <http://192.168.15.102/admin/advanced> G8 Hyperlinks >>

Google G Go Bookmarks 14 blocked Check AutoLink AutoFill Send to Settings

Refer Target Bye Delay:	0	Sticky 183:	no
<b>Call Feature Settings</b>			
Blind Attn-Xfer Enable:	no	MOH Server:	
Message Waiting:	no	Auth Page:	no
Default Ring:	1	Auth Page Realm:	
Conference Bridge URL:		Auth Page Password:	
Mailbox ID:		Voice Mail Server:	
State Agent:		CFWD Notify Serv:	no
CFWD Notifier:			
<b>Proxy and Registration</b>			
Proxy:	gw1.fonet.dk	Use Outbound Proxy:	no
Outbound Proxy:		Use OB Proxy In Dialog:	yes
Register:	yes	Make Call Without Reg:	no
Register Expires:	3600	Ans Call Without Reg:	no
Use DNS SRV:	no	DNS SRV Auto Prefix:	no
Proxy Fallback Intvl:	3600	Proxy Redundancy Method:	Normal
<b>Subscriber Information</b>			
Display Name:	Dit navn	User ID:	Brugernavn
Password:	Adgangskode	Use Auth ID:	yes
Auth ID:	Brugernavn		
Mini Certificate:			
SRTP Private Key:			
<b>Audio Configuration</b>			
Preferred Codec:	G711a	Use Pref Codec Only:	no
G729a Enable:	yes	G723 Enable:	yes
G726-16 Enable:	yes	G726-24 Enable:	yes
G726-32 Enable:	yes	G726-40 Enable:	yes
Release Unused Codec:	yes	DTMF Process AVT:	yes
Silence Supp Enable:	no	DTMF Tx Method:	Auto
<b>Dial Plan</b>			
Dial Plan:	(x.*x.)		
Enable IP Dialing:	yes		

Undo All Changes Submit All Changes

[User Login](#) [basic](#) | [advanced](#)

Copyright © 2003-2005 Sipura Technology. All Rights Reserved.

Start D:\Documents a... Inbox - Microso... FONET IP telefo... Sipura SPA Co... https://www.on... jp.dk - JP - Pack... Document1 - Mi... Document3 - Mi... 10:12

**Bemærk: Dial-Plan sættes til: (xx.\*x.|\*xx.\*x.)**



